ME-3000-GTU

Mecer 3000VA ON-LINE UPS (with AVR,Monitoring Software + Cable & Built-in Surge Protection) - Black

Product Overview

Mecer 3000VA ON-LINE UPS (with AVR,Monitoring Software + Cable & Built-in Surge Protection) - Black



Specifications

Overview:

Mecer 3000VA ON-LINE UPS (with AVR,Monitoring Software + Cable & Built-in Surge Protection) - Black

Features:

- True double-conversion
- Microprocessor control optimizes reliability
- Input power factor correction
- Output power factor 0.8
- Wide input voltage (110 V-300 V)
- Converter mode available
- ECO mode for energy saving
- Generator compatible
- Charger capacity expansion to 6A for long-run models
- Smart SNMP works well with either USB or RS-232 together
- Comprehensive display allows easy monitoring and access of UPS status

Specifications:

© 2016 Respective owners and brand holders. This table has been carefully researched and generated by ComXpert International CC (http://www.comx.co.za), however, errors and omissions may occur. Only references to South Africa apply. All products are sourced in South Africa from the official suppliers and the warranty is that of the local supplier. E&OE. This table and our site's content may be used on condition that this notice and link remains intact and unaltered.

Specifications

Product Code	ME-3000-GTU
SKU	ME-3000-WTU / ME-3000-GTU
WEIGHT	28
PHYSICAL DIMENSIONS	419 X 190 X 318 (mm)
CAPACITY	3000 VA / 2400 W
VOLTAGE RANGE LOW LINE TRANSFER	160VAC/140VAC/120VAC/110VAC+/-5% (based on load percentage 100% - 80 % / 80 % - 70 % / 70 - 60 % / 60 % - 0)
VOLTAGE RANGE LOW LINE COMEBACK	168VAC/148VAC/128VAC/118VAC +/- 5 % (based on load percentage 100% - 80 % / 80 % - 70 % / 70 - 60 % / 60 % - 0)
VOLTAGE RANGE HIGH LINE TRANSFER	300 VAC +/- 5 %
VOLTAGE RANGE HIGH LINE COMEBACK	290 VAC +/- 5 %
FREQUENCY RANGE	40Hz ~ 70 Hz
PHASE	Single phase with ground
POWER FACTOR	0.99 @ nominal voltage (input voltage)
OUTPUT VOLTAGE	200/208/220/230/240VAC
AC VOLTAGE REGULATION (BATT. MODE)	+/-1% (Batt. Mode)
FREQUENCY RANGE (SYNCHRONIZED RANGE)	47 ~ 53 Hz or 57 ~ 63 Hz
FREQUENCY RANGE (BATT. MODE)	50 Hz +/- 0.25 Hz or 60Hz +/- 0.3 Hz
OVERLOAD	100%~110%:audible warning 110%~130%: UPS shuts down in 60 seconds at battery mode or transfer to bypass when the utility is normal >130%:UPS shuts down immediately at battery mode or transfer to bypass mode when the utility is normal
CURRENT CREST RATIO	3:1
HARMONIC DISTORTION	3 % THD (linear load) 6 % THD (non-linear load)
WAVEFORM (BATT. MODE)	Pure Sinewave
AC TO DC	Zero
INVERTER TO BYPASS	4 ms (Typical)
AC MODE	0.9
BATTERY MODE	0.89
BATTERY TYPE	12 V / 9 AH
NUMBERS	6
RECHARGE TIME	4 hours recover to 90% capacity (Typical)
CHARGING CURRENT	1.0 A (max.)
CHARGING VOLTAGE	82.1 VDC +/-1%
BATTERY TYPE & NUMBERS	Depending on the capacity of external batteries
CHARGING CURRENT	1.0A/2.0A/4.0A/6.0 A +/-10%

CHARGING VOLTAGE	82.1 VDC +/-1%
HUMIDITY	20-90 % RH @ 0- 40 degreesC (non-condensing)
NOISE LEVEL	Less than 50dBA @ 1 Meter
OPTIONAL USB/RS-232 PORT	Supports Windows 2000/2003/XP/Vista/2008/7, Linux, Unix, and MAC
OPTIONAL SNMP	Power management from SNMP manager and web browser

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page:
https://www.comx-computers.co.za/ME-3000-GTU-Mecer-3000VA-ON-LINE-UPS-with-AVR-Monitoring-Software-Cable-Built-in-p-153360.php

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: https://www.comx-computers.co.za/terms-of-use.php
Terms of Sale: https://www.comx-computers.co.za/terms-of-sale.php

PDF generated: 2026-11-11 02:49:35.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.