ComX Computers
Product Specification Sheet


RB5009UPR+S+IN


MikroTik RouterBOARD RB5009 with 1x 2.5Gbit LAN & 7 x Gigabit LAN & 1x SFP+ Port

Product Overview

MikroTik RouterBOARD RB5009 with 1x 2.5Gbit LAN & 7 x Gigabit LAN & 1x SFP+ Port, 1x 2.5Gbit LAN (802.3af/at PoE-out and PoE-in), 7x 1Gbit LAN (802.3af/at PoE-out and PoE-in), 1x SFP+ Port, RouterOS L5, Metal Desktop case, RB5009UPR+S+IN, RouterOS license 5, 130 total Output Power









Specifications

Overview:

RB5009UPr+S+IN

A new version of our popular heavy-duty RB5009 router with PoE-in and PoE-out on all ports. Perfect for small and medium ISPs. 2.5 Gigabit Ethernet & 10 Gigabit SFP+, numerous powering options.

Its all about the power.

This version of the RB5009 has all the bells and whistles of the previous model: Gigabit Ethernet, 2.5 Gigabit Ethernet, and a 10 Gigabit SFP+ cage for fiber connectivity. It has the speed, the power, and the durability. But this time, we have added PoE-in & PoE-out on all eight Ethernet ports. Combined with the 2-pin connector and the DC jack, youre getting 10 separate ways of powering. Dual redundant power supplies would usually take your uninterrupted uptime to the next level. RB5009UPr+S+IN takes it one step above that!

All power options support a wide voltage range of 24 - 57 V . However, you can not mix the voltages. If youre using PoE-out to power other devices, the board will choose the source with the highest voltage (DC jack or the 2-pin connector) to power

those.

Each PoE-out port can supply up to 25W of power . All the ports combined are limited to 130W, which should be enough for most setups. You can specify maximum available power from your power sources manually, if necessary. When it comes to PoE-out features, the new RB5009 can trade blows with our legendary PoE switches: CRS354 & CRS328 . In the smallest possible form-factor and for the best price on the market!

Protect your uptime, protect your tranquility!

So what exactly happens if there is a problem with one of your power sources? Heres a quick example: you have 24V on the DC jack, 48V on the 2-pin connector, and 57V on the PoE-in. The board itself gets powered by the highest voltage input - the PoE-in. If theres a problem, RB5009 will fall back to the second highest voltage - the 2-pin connector. And if that fails - theres the 24V option on the DC jack.

What about the PoE-out devices? Once again - the highest voltage wins. PoE-out devices will draw power from the 48V source on the 2-pin connector. If that fails - the 24V on the DC jack come into play. The board will always reserve 20 watts to power itself. If there is not enough power for all the PoE-out ports, it will start disabling the ones with the lowest priority. You can set the port priority manually.

This tiny form-factor shines anywhere: from confined research facilities and offices to huge corporate server rooms. And dont forget that you can mount FOUR of these routers in a single 1U rackmount space

With the new RB5009, we want to empower all the small and medium ISPs that are always on the lookout for the most cost-effective and robust solutions. It is a perfect addition to our previous GPEN devices - a line of products designed to replace the expensive GPON solutions.

Specifications:

© 2023 Respective owners and brand holders. This table has been carefully researched and generated by ComXpert International CC (http://www.comx.co.za), however, errors and omissions may occur. Only references to South Africa apply. All products are sourced in South Africa from the official suppliers and the warranty is that of the local supplier. E&OE. This table and our site's content may be used on condition that this notice and link remains intact and unaltered.

Specifications	
Product Code	RB5009UPR+S+IN
Specifications	
Product code	RB5009UPr+S+IN
Architecture	ARM 64bit
CPU	88F7040
CPU core count	4
CPU nominal frequency	350-1400 (auto) MHz
RouterOS license	5
Operating System	RouterOS (v7 only)
Size of RAM	1 GB
Storage size	1 GB
Storage type	NAND
MTBF	Approximately 200'000 hours at 25C
Tested ambient temperature	-40 degreesC to 60 degreesC
Powering	
Number of DC inputs	3 (DC jack, PoE-IN, 2-pin terminal)
DC jack input Voltage	24-57 V

2-pin terminal input Voltage	24-57 V
Max power consumption	150 W
Max power consumption without attachments	15 W
Cooling type	Passive
PoE in	802.3af/at
PoE in input Voltage	24-57 V
PoE-out	
PoE-out ports	Ether1-Ether8
PoE out	802.3af/at
Max out per port output (input 18-30 V)	640 mA
Max out per port output (input 30-57 V)	420 mA
Max total out (A)	2.59 A
Total output current	2.28
Total output power	130
Ethernet	
10/100/1000 Ethernet ports	7
Number of 1G Ethernet ports with Reverse PoE (PoE-in)	7
Number of 2.5G Ethernet ports	1
Fiber	
SFP+ ports	1
Peripherals	
Number of USB ports	1
USB Power Reset	Yes
USB slot type	USB 3.0 type A
Max USB current (A)	1
Other	
CPU temperature monitor	Yes
Current Monitor	Yes
PCB temperature monitor	Yes
Voltage Monitor	Yes
Certification & Approvals	
Certification	CE, EAC, ROHS
IP	20

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page:
https://www.comx-computers.co.za/RB5009UPR-S-IN-MikroTik-RouterBOARD-RB5009-with-1x-2-5Gbit-LAN-7-x-Gigabit-LAN-1x-p-292508.php

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: https://www.comx-computers.co.za/terms-of-use.php
Terms of Sale: https://www.comx-computers.co.za/terms-of-sale.php

PDF generated: 2026-11-20 06:06:05.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.