

MT-RBCRS318-16P-2S+OUT

MikroTik netPower 16P 16x PoE ouput & 2x SFP+ outdoor Switch

Product Overview

MikroTik netPower 16P 16x PoE ouput 7 2x SFP+ outdoor Switch, CRS318-16P-2S+OUT, 16x 10/100/1000 Ethernet ports, Pole-mount, RouterOS L5, 802.3af/at PoE Output on ports 1 to 16, 2x 1.25Gbps SFP ports



Specifications

Overview:

MikroTik's RB-NETPOWER16P is an outdoor 18 port switch. It has 16x Gigabit Ethernet Ports, with PoE-out, and 2x SFP+ ports for 10G fibre uplinks. The sturdy and compact design allows this switch to be mounted in various environments, from damp attics and shafts to towers, masts and poles with the included hose clamps.

****Note: A power supply is not included with this product and must be purchased separately.**

Specifications:

© 2021 Respective owners and brand holders. This table has been carefully researched and generated by ComXpert International CC (<http://www.comx.co.za>), however, errors and omissions may occur. Only references to South Africa apply. All products are sourced in South Africa from the official suppliers and the warranty is that of the local supplier. E&OE. This table and our site's content may be used on condition that this notice and link remains intact and unaltered.

Specifications

Product Code	MT-RBCRS318-16P-2S+OUT
--------------	------------------------

ComX Computers

Product Specification Sheet

Product code	CRS318-16P-2S+OUT
CPU	98DX226S, 800 MHz
CPU temperature monitor	Yes
Size of RAM	256 MB
Storage	16 MB flash
Switch chip model	98DX226S
Number of 1G Ethernet ports	16
Number of 10G SFP+ ports	2
Operating system	RouterOS (License level 5) / SwOS (dual boot)
Dimensions	303 x 212 x 78 mm
Operating temperature	-40 degreesC to +70 degreesC
Powering	
PoE-out	Passive PoE with auto sensing, 802.3af/at
PoE-out ports	Ether1 - Ether16
Max PoE-out on low (< 30 V) voltage	5.6 A (2.8 A per 8port group, max 1.1 A per port)
Max PoE-out on high (> 30 V) voltage	2.8 A (1.4 A per 8port group, max 0.6 A per port)
Max total out (A)	The total output power limit will also depend on your power supply max current limit. You should not exceed your power supply current limit or the board may reboot
Number of DC jacks	2
Supported input voltage	18-30 V / 48- 57 V
Max power consumption	316 W
Max power consumption without attachments	16 W

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page:

<https://www.comx-computers.co.za/MT-RBCRS318-16P-2S-OUT-MikroTik-netPower-16P-16x-PoE-Buy-p-253205.php>

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: <https://www.comx-computers.co.za/terms-of-use.php>

Terms of Sale: <https://www.comx-computers.co.za/terms-of-sale.php>

PDF generated: 2026-10-08 10:22:59.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

ComX Computers

Product Specification Sheet

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.