ComX Computers
Product Specification Sheet

NET-MC100CM

TP-Link MC100CM Fast Ethernet Media Converter

Product Overview

TP-Link MC100CM Fast Ethernet Media Converter, Full-duplex,up to 2Km, switching power adapter, chassis mountable



Specifications

Overview:

The MC100CM is a media converter designed to convert 100BASE-FX fiber to 100Base-TX copper media or vice versa. Designed under IEEE 802.3u 10/100Base-TX and 100Base-FX standards, the MC100CM is designed for use with multi-mode fiber cable utilizing the SC-Type connector. The MC100CM supports longwave (LX) laser specification at a full wire speed forwarding rate. It works at 1310nm on both transmitting and receiving data. Other features of this module include the ability to be used as a stand alone device (no chassis required) or with TP-LINK´s 19"system chassis, Auto MDI/MDI-X for TX port, Auto negotiation of duplex mode on TX port and front panel status LEDs. The MC100CM will transmit at extended fiber optic distances utilizing multi-mode fiber up to 2 kilometers.

Features:

- Auto negotiation of 10/100Mbps and auto MDI/MDIX for TX port
- Provide switch configuration of Half-Duplex / Full-Duplex transfer mode for FX port
- Link Fault Passthrough and Far End Fault minimize the loss caused by link failure timely
- Extend fiber distance up to 2km
- Easy-to-view LED indicators provide status to monitor network activity easily
- External power supply

Specifications:

© 2018 Respective owners and brand holders. This table has been carefully researched and generated by ComXpert International CC (http://www.comx.co.za), however, errors and omissions may occur. Only references to South Africa apply. All products are sourced in South Africa from the official suppliers and the warranty is that of the local supplier. E&OE. This table and our site's content may be used on condition that this notice and link remains intact and unaltered.

Specifications	
Product Code	NET-MC100CM
Standards and Protocols	IEEE 802.3, IEEE 802.3u, IEEE 802.3x

Basic Function	Half/Full-Duplex transfer mode for FX port
	Full Duplex Flow Control (IEEE 802.3x)
	Half Duplex Flow Control (Backpressure)
	Extends fiber distance up to 2km
	Link Fault Passthrough and Far End Fault minimize the loss caused by link failure timely
Ports	1 100M SC/UPC port
	1 100M RJ45 port (Auto MDI/MDIX)
Wave Length	1310nm
Network Media 10BASE-T	UTP category 3, 4, 5 cable (maximum 100m)
	EIA/TIA-568 100ohm STP (maximum 100m)
Network Media 100BASE-T	UTP category 5, 5e cable (maximum 100m)
	EIA/TIA-568 100ohm STP (maximum 100m)
Network Media 100BASE-FX	Multi-mode Fiber
LED Indicators	PWR, FDX/Col, Link/Act, SPD
Dimensions (W*D*H)	3.7*2.9*1.1 in. (94.5*73.0*27.0 mm)
Power Supply	External power supply
Max Power Consumption	2.5W
Safety & Emission	FCC, CE, RoHS
Environment	Operating Temperature: 0 ~40 (32 ~104)
	Storage Temperature: -40 ~70 (-40 ~158)
	Operating Humidity: 10%~90% non-condensing
	Storage Humidity: 5%~90% non-condensing

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page:
https://www.comx-computers.co.za/NET-MC100CM-TP-Link-MC100CM-Fast-Ethernet-Media-Converter-p-197583.php

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: https://www.comx-computers.co.za/terms-of-use.php
Terms of Sale: https://www.comx-computers.co.za/terms-of-sale.php

PDF generated: 2026-11-09 18:01:40.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.