

POE400

Cudy POE400 90W Gigabit PoE+ Injector

Product Overview

Cudy POE400 90W Gigabit PoE+ injector, 10/100/1000 Mbps pass through Data rates, Output power voltage : 56VDC, 90W user Port power



Specifications

Overview:

90W Gigabit PoE/PoE+/PoE++ Injector POE400

- Full IEEE 802.3af IEEE 802.3at, IEEE 802.3bt Compliant
- Up to 90W of Power on 4-pairs
- Auto detect of POE IEEE 802.3af IEEE 802.3at, IEEE 802.3bt equipment
- Supports 10/100/1000Base-T applications
- LED indicators power input indication
- Distance up to 100 meters
- Internal AC/DC converter - no need for external power modules
- Easy plug-and-play installation
- Surge protection

Features:

PoE / 802.3af

Each PoE port powers up to 15W at a very short distance. Power delivered at a longer distance (up to 100m) is 12.95W. Typical devices needing less than 12.95W are:

- IP Phones with small or no display
- Indoor Wireless 802.11n or 2x2 Wireless 802.11ac Access Points
- Simple IP Cameras

PoE+ / 802.3at

Each PoE+ port powers up to 30W(2 Pair) or 60W(4 Pair) at a very short distance. Power delivered at a longer distance (up to 100m) is 25.5W or 51W(4 Pair). Typical devices are:

- IP Phones with a large display, video phones, conference systems

ComX Computers

Product Specification Sheet

- Up to 4x4 Wireless 802.11ac (WiFi 5) or 2x2 802.11ax (WiFi 6) Access Points
- Pan-Tilt-Zoom HD IP Cameras without heaters

PoE++ / 802.3bt

Each PoE++ port powers up to 60W(2 Pair) or 90W (4 Pair) at a very short distance. Power delivered at a longer distance (up to 100m) is 51W(2 Pair) or 71W (4 Pair). Typical devices are:

- Conference systems with a large display
- Up to 4x4 802.11ax (WiFi 6) Access Points
- PTZ HD IP Cameras with heaters
- AV over IP encoders/decoders
- Ceiling tiles LED Lighting
- Large audio speakers

Specifications:

© 2022 Respective owners and brand holders. This table has been carefully researched and generated by ComXpert International CC (<http://www.comx.co.za>), however, errors and omissions may occur. Only references to South Africa apply. All products are sourced in South Africa from the official suppliers and the warranty is that of the local supplier. E&OE. This table and our site's content may be used on condition that this notice and link remains intact and unaltered.

Specifications

Product Code	POE400
Model	POE400
No. of channels	1
Pass Through Data Rates	10/100/1000Mbps
Power over Ethernet Output	Pin Assignment and Polarity: 1/2 (-), 3/6 (+), 4/5 (+), 7/8 (-)
	Output Power Voltage: 56Vdc
	User Port Power: 90W
Input Power Requirements	AC Input Voltage: 100 to 240 VAC
	AC Input Current: 1A 100-240 VAC
	AC Frequency: 50 to 60 Hz
Dimensions	178.5mm x 80mm x 46mm
Indicators	System Indicator: AC Power
	User Indicator: Channel Power
Connectors	Shielded RJ-45, EIA 568A and 568B
Protection	Over current protection
	Over load protection
	Over voltage protection
	Anti-interference protection
Regulatory Compliance	IEEE 802.3af (15.4W)
	IEEE 802.3at (30W)
	IEEE802.3bt (90W)

ComX Computers

Product Specification Sheet

Environmental Conditions	Operating Ambient Temperature:0 to 45 degreesC
	Operating Humidity:Maximum 80%, Non-condensing
	Storage Temperature:-20 to 70 degreesC
	Storage Humidity:Maximum 80%, Non-condensing

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page: <https://www.comx-computers.co.za/POE400-Cudy-POE400-90W-Gigabit-PoE-Injector-Buy-p-264545.php>

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: <https://www.comx-computers.co.za/terms-of-use.php>

Terms of Sale: <https://www.comx-computers.co.za/terms-of-sale.php>

PDF generated: 2026-10-05 08:10:54.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.