

UPAPP5BV-SA

APC Essential SurgeArrest 5 outlets with Coax Protection

Product Overview

APC Essential SurgeArrest 5 outlets with Coax Protection 230V South Africa



Specifications

Features:

Manual disconnect switch

Enables the surge suppressor to be de-energized for service without disconnecting the protected load.

Transformer Block Spacing

Connect bulky transformer block plugs without covering up other outlets.

Right Angle Plug

Plug angle allows for equipment and furniture to be placed closer to the wall than with a standard power cord. Reduces cord stress too.

180 degree Rotating Cord Retainer

A 180-degree rotating cord with strain relief offers flexibility in positioning the SurgeArrest, and in routing the power cord.

Cord management

Reduces cord clutter.

Lightning and Surge Protection

To prevent damage to your equipment from power surges and spikes.

IEEE let-through ratings and regulatory agency compliance

Stringent third-party testing gives you confidence that APC's surge protectors will safeguard your equipment and data from potentially damaging surges and spikes.

Noise Filtering

Attenuates EMI/RFI line noise that can cause data errors and keyboard lockups, ensuring better performance of protected equipment.

Catastrophic Event Protection

SurgeArrest components such as MOVs and Thermal fuse ensure instantaneous reaction to lightning strikes and wiring faults. If the surge components are damaged due to power spike or over voltage, excess power cannot reach your equipment. Unlike the APC SurgeArrest products, most surge suppressors continue to let power through even after circuits have been damaged, leaving your equipment exposed to other damaging surges.

Fail Safe Mode

Most other surge suppressors continue to let power through even after their circuits have been damaged, leaving your equipment exposed to future surges. APC's SurgeArrest fail safe, which means that once the circuit of an APC SurgeArrest has been compromised the unit disconnects equipment from the power supply ensuring that no damaging surges reach your equipment.

Protection Working Indicator

SurgeArrest will warn you if its circuitry has been damaged by heavy strike or power line surge and it is unable to provide 100% protection. If still under warranty, APC will then replace your damaged SurgeArrest free of charge.

Building Wiring Fault Indicator

This LED informs users of potentially dangerous wiring problems in the wall circuit.

Specifications:

Output	
Number of Outlets	5
Receptacle Style	India/South Africa
Input	
Nominal Input Voltage	230V
Input Frequency	50/60 Hz
Input Connections	Indian/South African BS 546A
Maximum Line Current per phase	13A
Cord Length	1.83 meters
Maximum Input Current	16A
Surge Protection and Filtering	
Surge energy rating	960 Joules
eP Joule Rating	1060
EMI/RFI Noise rejection (100 kHz to 10 MHz)	30 dB
Peak Current Normal Mode	13 kAmps
Peak Current Common Mode	13 kAmps
Data Line Protection	Co-axial Video / Cable protection
Let Through Voltage Rating	< 900
Physical	
Net Weight	0.70 KG
Maximum Height	451.00 mm

ComX Computers

Product Specification Sheet

Maximum Width	83.00 mm
Maximum Depth	45.00 mm
Color	Charcoal
Environmental	
Operating Environment	0 - 40 degreesC
Operating Relative Humidity	0 - 95%
Operating Elevation	0-15000 meters
Storage Temperature	-15 - 45 degreesC
Storage Relative Humidity	0 - 95%
Storage Elevation	0-15000 meters
Conformance	
UL 1449 TVSS Rating	--V

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page:

<https://www.comx-computers.co.za/UPAPP5BV-SA-APC-Essential-SurgeArrest-5-outlets-with-Buy-p-25632.php>

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: <https://www.comx-computers.co.za/terms-of-use.php>

Terms of Sale: <https://www.comx-computers.co.za/terms-of-sale.php>

PDF generated: 2026-10-16 06:20:08.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.