UPS-ONL-1KVA-RX-LQ

Linkqnet 1kva Xrt 800w Online 2u Rack Ups 24vdc (No Batteries)

Product Overview

Linkqnet 1kva Xrt 800w Online 2u Rack Ups 24vdc (No Batteries)



Specifications

Overview:

High Power-Density Rackmount Online UPS

Features:

- True double-conversion pure sinewave output
- Microprocessor control optimizes reliability
- Input power factor correction
- Output power factor 0.8
- Wide input voltage (110V - 300V)
- Converter mode available
- ECO mode for energy saving
- Generator compatible
- Cold Start function
- USB and RS-232 Communication with free multiple server power control software
- Optional WEB/SNMP Network Card for remote monitoring and control
- LCD display allows easy monitoring and access of UPS status
- ESD / Surge protection and two year warranty on electronics

Specifications:

SPECIFICTATIONS	
INPUT	230 VAC - Single Phase with Ground
Voltage	110 - 300 VAC @ 50% load
Voltage Range	160 - 280 VAC @ 100% load
	40Hz - 70Hz

Frequency Range	>= 0.99 at 100% Load and Nominal Input Voltage
Power Factor	
Input Socket Type	IEC C14
Input Over-Current Protection	Circuit Breaker (Manually Resettable)
Input Surge / Lightning Protection	400V Metal-oxide Varistors
OUTPUT	1000 VA / 800 W
Continious Output Power	230 VAC (Programmable - 200/208/220/240 VAC)
Default Output Voltage	+/- 1%
Voltage Regulation	47 Hz - 53 Hz
Frequency Range (Synchronised)	50 Hz +/- 0.25 Hz (or 60 Hz +/- 0.3 Hz in converter mode)
Frequency Range (Battery Mode)	3::1
Current Crest Ratio	
Harmonic Distortion	
	Zero
Transfer Time - AC to Inverter Mode	4 ms (Typical)
Transfer Time - Inverter to Bypass	Pure Sinewave
Waveform	IEC C13 (3 x sockets)
Output Socket Type	
EFFICIENCY	0.88
AC Mode	0.83
Battery Mode	
INDICATORS	Status, Load Level, Battery Level, Input/Output Voltage, Discharge Timer and Fault Condition
LCD	
Dimensions	310 x 438 x 88 mm
	12 kg
ALARM	Sounding every 4 seconds
Mains Fail / Battery Mode Alarm	Sounding every 1 second
Low Battery Alarm	Twice every second
Overload Alarm	Continuously sounding
Fault Alarm	Yes - Mains Fail / Battery alarm via front panel
Alarm Silence	Yes - Supports Windows, Linux, Synology and MAC
RS-232 Serial Port Monitoring	Yes - Supports Windows, Linux, Synology and MAC
USB Port Monitoring	Option - Supports full remote network management
WEB / SNMP Network Slot	
OPTIONS	Enables the UPS to be installed into a network rack
Optional Rackmount Rail Kit	Enables the UPS to be bypassed and fully isolated
Optional Static Bypass Switch	Enables a direct connection to the PC or Server

IEC Male / Female Power Cord	Allows you to connect normal RSA plugs to the UPS

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page:
https://www.comx-computers.co.za/UPS-ONL-1KVA-RX-LQ-Linkqnet-1kva-Xrt-800w-Online-2u-Rack-Ups-24vdc-No-Batteries-p-293752.php

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: https://www.comx-computers.co.za/terms-of-use.php
Terms of Sale: https://www.comx-computers.co.za/terms-of-sale.php

PDF generated: 2026-11-12 03:00:16.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.