

560443

Intellinet POE Splitter

Product Overview

Intellinet POE Splitter, IEEE802.3at, 5, 7.5, 9 or 12 V DC output current, Colour: Black

ComX Computers



ComX Computers



ComX Computers



ComX Computers



ComX Computers



Specifications

Overview:

ComX Computers

Product Specification Sheet

The INTELLINET NETWORK SOLUTIONS PoE Splitter allows you to deliver both data and electrical power to non-PoE Ethernet-enabled products using the Cat5 Ethernet cable. Using the PoE Splitter, you can take advantage of Power over Ethernet and place Ethernet-enabled products, such as Network Cameras and Wireless Access Points, where power outlets are not readily available.

Simplify Installation for an Ethernet-based Device

Having to manage only an Ethernet cable simplifies the physical installation of the device. Without having to worry about the availability of a power source, you can mount Ethernet-enabled products on a ceiling or outdoors, up to 100m (328 feet) from a power source. The PoE Splitter is simple to install and requires no tools or software.

802.3af Compliant Power over Ethernet

The PoE Splitter can be used to complement any PoE injector unit or midspan switch to provide small to medium-sized businesses a complete end-to-end PoE solution. This unit supports 802.3af and 802.3at, ensuring compatibility with other 802.3af/t PoE-compliant injector units or PSE switches.

Adjustable Power Output

During the setup, the PoE Splitter can be set to power any compatible 5 V, 7.5 V, 9 V or 12 V Ethernet-enabled device via the volt selector located on the side.

Features:

- IEEE 802.3af-compliant PoE splitter
- Can be used to connect non-PoE IEEE 802.3af/t-compliant devices to a PoE injector or PoE switch
- Output current, selectable: 5, 7.5, 9 or 12 V DC
- Power output: 5 V / 4 A, 7.5 V / 2.7 A, 9 V / 2.3 A and 12 V / 1.7 A
- 10/100 auto-sensing input port automatically detects optimal network speeds
- RJ45 input port with Auto-MDIX and NWay auto-negotiation support
- Full/half duplex operation
- Compact metal case
- LED for link on PoE input port

Specifications:

Standards	IEEE 802.3af (Power over Ethernet)
	IEEE 802.3at (High-Power PoE Power over Ethernet)
	IEEE 802.3 (10Base-T Ethernet)
	IEEE 802.3u (100Base-TX Fast Ethernet)
General	Media support:
	- 10Base-T Cat3, 4, 5 UTP/STP RJ45
	- 100Base-TX Cat5 UTP/STP RJ45
	Ports:
	- 1 RJ45 10/100 Mbps input port for 48 V IEEE 802.3af-compliant signal
	- 1 RJ45 10/100 Mbps output port
	- 1 power output port
LEDs	Certifications: FCC Class A, CE
	LINK

ComX Computers

Product Specification Sheet

Power	Output power:
	- 5, 7.5, 9 or 12 V DC, selectable via switch
	- Maximum output: 5 V - 4 A, 7.5 V - 2.7 A, 9 V - 2.3 A, 12 V - 1.7 A
	- Polarity, outer: negative (-); inner: positive ()
	Power consumption: 25.4 Watts (maximum)
Environmental	Metal housing
	Dimensions: 102 (L) x 74 (W) x 22 (H) mm (4.0 x 2.9 x 0.9 in.)
	Weight: 0.24 kg (0.5 lbs.)
	Operating temperature: 0 - 60 degreesC (32 - 140 degreesF)
	Operating humidity: 10 - 90% RH, non-condensing
	Storage temperature: -20 - 90 degreesC (-4 - 194 degreesF)
Package Contents	PoE Splitter
	Power output cable
	User manual

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page: <https://www.comx-computers.co.za/560443-Intellinet-POE-Splitter-Buy-p-62989.php>

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: <https://www.comx-computers.co.za/terms-of-use.php>

Terms of Sale: <https://www.comx-computers.co.za/terms-of-sale.php>

PDF generated: 2026-10-05 05:19:22.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.