**ComX Computers**
Product Specification Sheet

# 5PX2200IRTN

Eaton 5PX 2200VA Tower/Rack 2U Line-Interactive UPS Netpack (Including SNMP)

## Product Overview

Eaton 5PX 2200VA Tower/Rack 2U Line-Interactive UPS




## Specifications

**Overview:**

The Eaton 5PX Rack/Tower UPS provides line-interactive backup power and scalable runtimes for servers, storage systems, VoIP gear and network equipment. With a next-generation intuitive LCD display, energy consumption metering down to the outlet group level, and up to 99% efficiency, the 5PX is the perfect UPS to protect modern IT equipment.

**Specifications:**

© 2014 Respective owners and brand holders. This table has been carefully researched and generated by ComXpert International CC (http://www.comx.co.za), however, errors and omissions may occur. Only references to South Africa apply. All products are sourced in South Africa from the official suppliers and the warranty is that of the local supplier. E&OE. This table and our site's content may be used on condition that this notice and link remains intact and unaltered.

| | |
|---|---|
| **Specifications** | |
| **Product Code** | 5PX2200IRTN |
| **General** | |
| **Topology** | Line-Interactive High Frequency (Pure Sinewave, Booster + Fader) |
| **Configuration** | Tower/Rack 2U |
| **Part Number** | 5PX2200iRTN |
| **Rating (VA/Watts)** | 2200/1980 |
| **Dimensions (H x W x D, mm)** | 86.2 x 441 x 522 |
| **Weight (kg)** | 28.5 |
| **Electrical Input** | |
| **Connection** | (1) IEC-320-C20 |
| **Input Cord** | Schoko to IEC C19 (1) |

| | |
|---|---|
| **Input Voltage Without Using Batteries** | 160V-294V (adjustable to 150V-294V) |
| **Input frequency Range Without Using Batteries** | 47 to 70 Hz (50 Hz system), 56.5 to 70 Hz (60 Hz system), 40 Hz in low-sensitivity mode |
| **Electrical Output** | |
| **Voltages** | 230 V (+6/-10 %) (Adjustable to 200V / 208V / 220V / 230V / 240V) |
| **Output Receptacles** | (8) IEC-320-C13 |
| | (1) IEC-320-C19 |
| **Remotely controlled sockets** | 2 groups of 2 x IEC C13 (10 A) |
| **Power Cables** | IEC C13-C14 (2) |
| **Output Frequency** | 50/60 Hz +/- 0.1 % (autosensing) |
| **Battery** | |
| **Battery Management** | ABM & Temperature compensated charging method (user selectable), Automatic battery test, deep discharge protection, automatic recognition of external battery units |
| **Communications** | |
| **Communication Ports** | 1 USB port + 1 RS232 serial port and relay contacts (USB and RS232 ports cannot be used simultaneously) |
| | + 1 mini terminal block for remote ON/OFF and Remote Power Off |
| **Communications Card Slots** | 1 slot for NMC Minislot card or NMC ModBus/JBus or MC Contacts/Serial |
| **Environmental & Standards** | |
| **Audible Noise** | < 45 dBA |
| **Operating Temperature** | 0 to 40 degreesC |
| **Performance - Safety - EMC** | IEC/EN 62040-1-1 (Safety), IEC/EN 62040-2 (EMC), IEC/EN 62040-3 (Performance), C-Tick |
| **Approvals** | CE, CB report, TÜV |

## Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

**Product page:**
**https://www.comx-computers.co.za/5PX2200IRTN-Eaton-5PX-2200VA-Tower-Rack-2U-Line-Interactive-UPS-Netpack-Including-p-99344.php**

*Images and specifications are provided for reference and are subject to change without notice. E&OE.*

Terms of Use: https://www.comx-computers.co.za/terms-of-use.php
Terms of Sale: https://www.comx-computers.co.za/terms-of-sale.php

PDF generated: 2026-11-10 09:43:43.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.