AJAX-SC-FOB-B

AJAX - SpaceControl Wireless Black Fob Remote

Product Overview

AJAX - SpaceControl Wireless Black Fob Remote, Up to 5 years battery life, Four Buttons, Support Panic Button, 1948527-04-BL1

Specifications

Overview:

Ajax SpaceControl

A key fob for controlling security modes. Features a panic button for sending alarms to your inner circle and a security company in case of trouble.

- Authentication to prevent forgery
- Jamming detection and communication channels encryption
- Two-way communication
- Calls for help in case of emergency
- Activates full or partial alarm modes
- Indicates command execution with color blink

Features:

Principle of operation

The device controls the security modes and sends an alarm signal to the Central Monitoring Station by pressing the key fob panic button.

Authentication prevents forgery of the device and false alarm signals.

Connecting and setting up

Ready to operate straight out the box: the battery is already installed, therefore there is no need to disassemble the detector. With one click, it can be connected to the hub in the mobile application.

Specifications:

© 2023 Respective owners and brand holders. This table has been carefully researched and generated by ComXpert International CC (http://www.comx.co.za), however, errors and omissions may occur. Only references to South Africa apply. All products are sourced in South Africa from the official suppliers and the warranty is that of the local supplier. E&OE. This table and our site's content may be used on condition that this notice and link remains intact and unaltered.

Specifications	
Product Code	AJAX-SC-FOB-B
Classification	Four-button key fob with command delivery indication
Compatibility	Operates with all Ajax hubs, range extenders, ocBridge Plus, uartBridge
Number of buttons	4
False alarm prevention	Yes, long press or double press (firmware version 5.54.1.0 or higher. Manufacture date from March 19, 2020)
Deactivation of the panic button	Available
Power supply	Battery: CR2032 battery, 3 V
Battery life	Up to 5 years
Jeweller radio technology	Communication range with central unit - up to 1,300 m in an open space
	Two-way communication between devices
	Radio frequency bands:
	866.0 - 866.5 MHz
	868.0 - 868.6 MHz
	868.7 - 869.2 MHz
	905.0 - 926.5 MHz
	915.85 - 926.5 MHz
	921.0 - 922.0 MHz
	(depends on the region of sale)
	Self-adjusting RF output power - up to 20 mW
	Block encryption based on AES algorithm
	Device polling period - 12-300 s
Operating temperature range	From -25 degrees? to +50 degrees?
Permissible humidity	Up to 95%
Dimensions	65 x 37 x 10 mm
Weight	13 g

Complete set	SpaceControl keyfob
	CR2032 battery (pre-installed)
	User's guide

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page:
https://www.comx-computers.co.za/AJAX-SC-FOB-B-AJAX-SpaceControl-Wireless-Black-Fob-Buy-p-284766.php

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: https://www.comx-computers.co.za/terms-of-use.php
Terms of Sale: https://www.comx-computers.co.za/terms-of-sale.php

PDF generated: 2026-10-20 05:09:23.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.