

ARCHER-MR400

TP-Link Archer MR400 AC1200 Wireless Dual Band 4G LTE Router

Product Overview

TP-Link Archer MR400 AC1200 Wireless Dual Band 4G LTE Router



Specifications

Features:

- Cutting-edge 4G network - share internet access with up to 64 Wi-Fi devices and enjoy download speeds of up to 150 Mbps
- AC1200 Wi-Fi - creates simultaneous dual band Wi-Fi networks, with maximum speeds of up to 300 Mbps on the 2.4 GHz band and 867 Mbps on the 5 GHz band
- Plug a SIM card and play - no configurations needed, compatibility for SIM cards in 100+ countries are assured by years of field tests
- Two detachable advanced LTE antennas - enjoy stable and efficient connections to every device thanks to the two external antennas
- Wi-Fi router mode - plug an Ethernet cable into the LAN/WAN port for flexible access as a backup option if you can't get a 4G connection

Got SIM Card? Then Plug and Play!

With an integrated 4G LTE modem and a built-in SIM card slot, all you need to do is insert a micro SIM card and turn on the Router. Enjoying fast, stable Wi-Fi on a 4G LTE network has never been easier.

Share Your 4G LTE Network

Take full advantage of your cutting-edge 4G LTE network for download speeds of up to 150 Mbps. Share your 4G LTE network with multiple Wi-Fi devices and enjoy uninterrupted HD movies, rapid file downloads, and smooth video chats. Fully compatible with FDD-LTE and TDD-LTE to work with most service providers worldwide.

Wi-Fi Where You Need It

Enjoy unmatched convenience and versatility. Tested in the field for years to ensure universal compatibility with 2 advanced LTE antennas to deliver a smooth connection. Simply plug in a micro SIM card and power on this elegant piece of technology to utilize fast and stable Wi-Fi, whether you're at home or working remote.

Internet Access for up to 64 Devices Simultaneously

Easily share a 3G/4G connection with up to 64 wireless devices, such as phones, tablets, and laptops, at the same time. 4 LAN ports stand ready to provide internet for wired devices like desktop computers.

ComX Computers

Product Specification Sheet

Easy Setup and Management

Set up the Archer MR400 in minutes thanks to its intuitive web interface and the powerful Tether app. Tether also lets you manage its network settings from any Android or iOS device, including parental controls and access control.

Specifications:

© 2023 Respective owners and brand holders. This table has been carefully researched and generated by ComXpert International CC (<http://www.comx.co.za>), however, errors and omissions may occur. Only references to South Africa apply. All products are sourced in South Africa from the official suppliers and the warranty is that of the local supplier. E&OE. This table and our site's content may be used on condition that this notice and link remains intact and unaltered.

Specifications

Product Code	ARCHER-MR400
HARDWARE FEATURES	
Interface	3 10/100Mbps LAN Ports, 1 10/100Mbps LAN/WAN Port
	1 Micro SIM Card Slot
Button	WPS/Reset Button, WiFi On/Off Button, Power On/Off Button
External Power Supply	12V/1A
Dimensions (W x D x H)	7.95 x 5.55 x 1.32 in. (202 x 141 x 33.6 mm)
Antenna	V2: 2 Internal 4G LTE Antennas
	V3/V1: 2 Detachable 4G LTE Antennas
WIRELESS FEATURES	
Wireless Standards	IEEE 802.11ac/n/a 5GHz, IEEE 802.11b/g/n 2.4GHz
Frequency	2.4GHz and 5GHz
Signal Rate	300Mbps at 2.4GHz, 867Mbps at 5GHz
Reception Sensitivity	5GHz: 11a 54M: -74dBm
	11ac HT20: -67dBm
	11ac HT40: -64dBm
	11ac HT80 : -60dBm
	11n HT20: -71dBm
	11n HT40: -70dBm
	2.4G: 11g 54M: -76dBm
	11n HT20: -73dBm
	11n HT40: -67dBm
Transmit Power	CE:
Wireless Functions	Enable/Disable Wireless Radio, WMM
	Wireless Statistics
WAN Failover	Yes
Wireless Security	64/128-bit WEP, WPA/WPA2, WPA-PSK/WPA2-PSK encryptions

ComX Computers

Product Specification Sheet

Network Type	4G: FDD-LTE B1/B3/B7/B8/B20 (2100/1800/2600/900/800MHz)
	TDD-LTE B38/B39/B40/B41 (2600/1900/2300/2500MHz)
	3G: DC-HSPA+/HSPA+/HSPA/UMTS B1/B8 (2100/900MHz)
SOFTWARE FEATURES	
Quality of Service	Bandwidth Control
Operating Modes	3G/4G Router, Wireless Router
WAN Type	Dynamic IP/Static IP/PPPoE/PPTP(Dual Access)/L2TP(Dual Access)
Management	Access Control, Local Management, Remote Management
	reboot schedule
DHCP	Server, Client, DHCP Client List, Address Reservation
Port Forwarding	Virtual Server, Port Triggering, UPnP, DMZ
Dynamic DNS	DynDns, NO-IP
VPN	PPTP VPN, IPsec VPN, OpenVPN
Access Control	Parental Control, Local Management Control
Firewall Security	DoS, SPI Firewall, IP Address Filter/Domain Filter
	IP and MAC Address Binding
Protocols	Supports IPv4 and IPv6
Guest Network	2.4GHz guest network x 1, 5GHz guest network x 1
IPsec VPN	Supports up to 10 IPsec VPN tunnels
OTHERS	
Certification	CE, RoHS
Package Contents	AC1200 Wireless Dual Band 4G LTE Router, Archer MR400
	RJ45 Ethernet Cable
	Power Adapter
	Quick Installation Guide
System Requirements	Microsoft Windows 98SE, NT, 2000, XP, Vista or Windows 7, 8, 8.1, 10
	MAC OS, NetWare, UNIX or Linux
	Internet Explorer 11, Firefox 12.0, Chrome 20.0,
	Safari 4.0 browsers or higher, or other Java-enabled browsers
	Micro SIM Card
Environment	Operating Temperature: 0 degreesC~40 degreesC (32 degreesF ~104 degreesF)
	Storage Temperature: -40 degreesC~70 degreesC (-40 degreesF ~158 degreesF)
	Operating Humidity: 10%~90% non-condensing
	Storage Humidity: 5%~90% non-condensing

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page:

<https://www.comx-computers.co.za/ARCHER-MR400-TP-Link-Archer-MR400-AC1200-Wireless-Dual-Buy-p-283425.php>

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: <https://www.comx-computers.co.za/terms-of-use.php>

Terms of Sale: <https://www.comx-computers.co.za/terms-of-sale.php>

PDF generated: 2026-10-19 22:27:19.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.