ComX Computers
Product Specification Sheet

DC UPS

Mecer 2600mAh battery On-line UPS (For WiFi / 3G / 4G Router)

Product Overview

Mecer 2600mAh battery On-line UPS (For WiFi / 3G / 4G Router), Built-in Li-ion battery



Specifications

Features:

- Built-in Li-ion battery
- Microprocessor control guarantees high reliability
- Manual power off switch
- Auto start when plugged in
- Multi-color indicator
- Overload, short-circuit, over-charge and over-discharge protection

MODEL ePower

AC INPUT

- Voltage Range 90 VAC ~ 264 VAC
- Frequency 50 or 60 Hz
- Surge protection 1.5KV (Optional K.21 enhanced, 6KV)

DC OUTPUT

- Voltage 12VDC +/- 5%
- Max. Power 25W (2.1A)

Battery

- Type Lithium-ion Battery
- Voltage 3.7VDC
- Capacity 2600mAh
- Typical Charging Time 3 hours recover to 90% capacity

Protection

- Battery Deep Discharge, Over-charge and Short Circuit Protection
- Input/Output Fuse for Short Circuit and Overload Protection

INDICATORS

- LED Full Battery Green lighting
- Battery Charging Constant flashing on Green LED

Battery

- Discharging Quick flashing on Green LED
- Fault Red lighting

PHYSICAL

- Input Plug Mounted on the housing (NEMA/UK/Schuko)
- Ouput Cable 1m Length (DC Male Jack, OD 4mm, ID 1.7mm or OD 5.5mm, ID 2.5mm)

Dimension

- D X W X H (mm) 68 x 42 x 74
- Net Weight (g) 280

Backup Time Table : (For Reference)

- 12V/1A Router 150 mins
- 12V/1.5A Router 120 mins
- 12V/2.0A Router 90 mins

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page:
https://www.comx-computers.co.za/DC-UPS-Mecer-2600mAh-battery-On-line-UPS-For-WiFi-3G-4G-Router-p-225542.php

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: https://www.comx-computers.co.za/terms-of-use.php
Terms of Sale: https://www.comx-computers.co.za/terms-of-sale.php

PDF generated: 2026-11-08 08:16:02.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.