ComX Computers
Product Specification Sheet

LG ARX5.DZAFLLK

LG ARX5 AV Receiver 1000W 4.2ch Home Theatre System

Product Overview

LG ARX5.DZAFLLK AV Receiver 1000W, 4.2ch, Satellite, TV Sound Sync, HDMI 3 IN 1 OUT, Multi BT, USB Playback, DJ Pro



Specifications

Features:

USB Direct Recording & Playback
With the LG Home Theater System, Micro and Mini Audio you can not only play files stored on USB devices, but record CD tracks or FM radio programs on your USB, while listening at the same time.

Wireless Audio Streaming
Enjoy your favorite music on mobile devices through LG sound system with wireless audio streaming via Bluetooth®.

Specifications:

© 2018 Respective owners and brand holders. This table has been carefully researched and generated by ComXpert International CC (http://www.comx.co.za), however, errors and omissions may occur. Only references to South Africa apply. All products are sourced in South Africa from the official suppliers and the warranty is that of the local supplier. E&OE. This table and our site's content may be used on condition that this notice and link remains intact and unaltered.

Specifications	
Product Code	LG ARX5.DZAFLLK
Amplifier	
Power Output (THD 10%) Total	1000W
Power Output (THD 10%) Front	167 X 2
Power Output (THD 10%) Surround	167 X 2
Power Output (THD 10%) Subwoofer	167 X 2
Function Aux	2
Function Portable IN	Yes

Function FM/AM/RDS	FM
Interface	
Audio Line IN Analog (AUX)	2
Audio Line IN Digital (Optical/Coaxial)	1/0
Audio Line OUT Analog Out	1
Output Terminal(Front/Center/Rear/2 Subwoofer) Terminal Type	Spring Push-in type (Subwoofer : Lan Type)
Video Signal IN	1
Video Signal OUT Composite	1
Video Signal OUT HDMI Out	1
Video Signal OUT HDMI Input	3
TV Sound ez Set-up	Yes
HD AV Sync	Yes
Portable In Jack(3.5Ø)	Yes
USB Jack	Yes
Bluetooth	Yes
Bluetooth Remote App	Yes
External FM/MW Antenna	Yes/No
MainSet Front Key	
Master Volume	Yes
Function	Yes
User EQ	Yes
Enter	Yes
Power On/Off	Yes
Sound Effect	Yes
Bass Blast (BASS)	Yes
Play/Pause	Yes
Stop	Yes
DJ Effect	Yes
DJ Control	Yes
Audio	
Sound Effect Dolby Digital	Yes
Sound Effect 2Ch Stereo(By-Pass)	No
Natural Plus (NAT-PLUS)	No
Natural EQ (NATURAL)	No
SMART DJ	No

Auto EQ	No
VSM+ (Virture) -> 3D SOUND	No
Bass Blast (BASS)	Yes
MP3 Optimizer (MP3 OPT)	No
Football	Yes
Loudness	No
User EQ	Yes
Local	No
Pop	Yes
Classic	Yes
Jazz	Yes
Rock	Yes
Auto DJ	Yes
Test Tone	Yes
Sound Level (Trim)	Yes
Mute	No
Display	FL
Dimmer	Yes
Sleep	Yes
Power	
SMPS	110-240 V~
Power Consumption	116W
Power Consumption at stand by	0.5W?
Tuner	
Type	PLL
Band	FM
Tuning Range (FM1/50 kHz, 100 kHz)	87.50~108.00 MHz(50kHz)
Station Preset	50 (Random)
Clear	Yes
External FM Antenna	Yes
DVD/CD/VCD Player, File Format	
USB MP3	Yes
USB MP3 ID3 Tag	Yes
File Format WMA	Yes
Convenience Repeat 1/ALL	Yes/Yes
Convenience Random Play	Yes

Convenience Skip - Fwd/Rev	Yes
Convenience Scan - Fwd/Rev	Yes
Convenience USB Direct Recording	Yes
Remote Cotrol Unit	
Tool X.	CB1
Battery (Size)	AAA x 1
Speaker	
System	4.2CH
Front Model Name	S63S1-S
Front SPL	81dB
Front System	Closed Type
Front Woofer Unit	3" Paper
Front Impedance	3ohm
Front Magnetic Shielding	Non-Shielded
Rear Model Name	S63S1-S
Rear SPL	81dB
Rear System	Closed Type
Rear Impedance	3ohm
Rear Magnetic Shielding	Non-Shielded
Subwoofer Model Name	S75T1-W
Subwoofer SPL	83dB
Subwoofer System	BASS REFLEX
Subwoofer Woofer Unit	7" Paper
Subwoofer Impedance	3ohm
Subwoofer Magnetic Shielding	Non-Shield
Accessories	
Instruction Manual	Yes
Remote Control Unit	Yes
FM Antenna	(75ohm)
Batteries	Yes
Warranty Card	Yes
RCA Code(Audio), Red/White, 2P	No
RCA Code(Video), Yellow, 1P	No
Coaxial Cable	No
HDMI Cable	No
Carton Box Type (Tip on / Offset / Flexo)	Flexo

Physical	
Size (W x H x D) mm - Main	430 x 147.5 x 368
Size (W x H x D) mm - Front Speaker	88 x 122 x 81
Size (W x H x D) mm - Rear Speaker	88 x 122 x 81
Size (W x H x D) mm - Subwoofer	191 x 388.5 x 318
Net Weight (Kg) - Main	4.7 kg
Net Weight (Kg) - Front Speaker	0.5
Net Weight (Kg) - Rear Speaker	0.5
Net Weight (Kg) - Subwoofer	5
Carton Size (W x H x D) mm	540 x 606 x 456
Gross Weight (Kg)	19.6
Container Q'ty (20ft)	162
Container Q'ty (40ft)	330

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page:
https://www.comx-computers.co.za/LG-ARX5-DZAFLLK-LG-ARX5-AV-Receiver-1000W-4-2ch-Home-Theatre-System-p-206950.php

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: https://www.comx-computers.co.za/terms-of-use.php
Terms of Sale: https://www.comx-computers.co.za/terms-of-sale.php

PDF generated: 2026-11-20 09:20:44.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.