

NBLE40ALLG2WWW

Lenovo Go USB-C Laptop Power Bank 20000 mAh

Product Overview

Lenovo 40ALLG2WWW Go USB-C Laptop Power Bank 20000 mAh, Li-ion battery Type, USB Type-C Laptop Power Delivery requirement Maximum 65W



Specifications

Overview:

The Lenovo Go USB-C Laptop Power Bank (20000 mAh) is a game-changing solution for remote workers who need access to a large reserve of power for their USB-C laptops and devices to achieve peak productivity. With a whopping 20,000 mAh capacity, you can rapidly charge multiple devices even while you are recharging the power bank.

Features:

- 20,000mAh capacity, 65W max. output
- Dual USB-C connection, 1 x USB-C port + 1 x USB-C integrated cable
- USB-C charging support power-in and power-out
- 1 x USB-A fast charging up to 18W
- Fast charge with any USB-C adapter, fully charged in 3 hours
- Simultaneously charging up to 3 devices
- Supports pass-through charging
- Compatible with any PD 3.0 devices
- Built-in overcharge and safety protection

Specifications:

© 2022 Respective owners and brand holders. This table has been carefully researched and generated by ComXpert International CC (<http://www.comx.co.za>), however, errors and omissions may occur. Only references to South Africa apply. All products are sourced in South Africa from the official suppliers and the warranty is that of the local supplier. E&OE. This table and our site's content may be used on condition that this notice and link remains intact and unaltered.

Specifications	
Product Code	NBLE40ALLG2WWW
Capacity	20000 mAh

ComX Computers

Product Specification Sheet

Color	Thunder Black
Battery Type	Li-ion (Polymer battery)
Weight	390 g (0.86 lbs)
Material	Plastic
Hardware Requirements	Supported laptops with USB-C charging port, USB C Laptop power delivery requirement max 65W
Output Power	USB-C - Max 65 W (20V/3.25A), USB-A - Max 18 W (12V/1.5A)
Brand	Lenovo
OS Requirements	OS Independent
Packed Weight	497 g
Agency Approvals	CB, CE, cTUVus, UN38.3, CEC
Charge-in Ports	1 x USB-C integrated cable, 1 x USB-C port
Charge-out Ports	1 x USB-C integrated cable, 1 x USB-C port, 1 x USB-A Port
Package Type	Gift box
Packed Dimensions (L x D x H)	107x32x221 mm
Height	23 mm (0.91 in)
Length	170 mm (6.69 in)
Depth	72 mm (2.83 in)
Special/Added Features	Supports simultaneous charging between power bank, laptop and mobile devices
Maximum Operating Temperature	35 degrees Celsius (95 degrees Fahrenheit)
Minimum Operating Temperature	0 degrees Celsius (-32 degrees Fahrenheit)
Maximum Relative Humidity (%)	90%
Minimum Relative Humidity (%)	8%
Battery Charging Time	3 Hours (Depends on power adapter used. Value measured using Lenovo 65W power adapter)
Battery Performance (Wh)	74 Wh
Included Accessory	NA
Input Power	100 W (20V/5A)
LED Indicator	4 LED @ 25% each
Power Button	Yes
Quick Charge	Yes
Safety Protection	Built in Over Voltage Protection (OVP) circuit, Built in Over Temperature (OTP) circuit Built in Over Current (OCP) circuit
Shipment Group	Lenovo USB-C Laptop Power Bank (20000 mAh), Warranty document, Quick Start Manual
Supported Operating Systems	OS Independent
General	Lenovo Go USB-C Laptop Power Bank (20000 mAh)

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page:

<https://www.comx-computers.co.za/NBLE40ALLG2WWW-Lenovo-Go-USB-C-Laptop-Power-Bank-20000-Buy-p-271344.php>

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: <https://www.comx-computers.co.za/terms-of-use.php>

Terms of Sale: <https://www.comx-computers.co.za/terms-of-sale.php>

PDF generated: 2026-10-09 13:00:06.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.