ComX Computers
Product Specification Sheet

RR-H6V2-13PK-R1

Coolermaster Hyper 612 V2 CPU Air Cooler

Product Overview

Coolermaster Hyper 612 V2, folding fin with air-guide + x-vents around heatpipes for better turbulence, copper base+ aluminium fin with 6x HDT/ DCH+CDC copper heatpipes (Heatpipe Direct Touch + Direct Contact Heatpipes + Continuous Direct Contact), 1x 120mm PWM fan, heatsink size: 140x128x163mm, Rifle bearing, 800-1300rpm, 26.6-44.2CFM, 11-20dba - for Intel LGA775/ 1155/ 1156/ 1366, AMD s754/940/ AMx/ socket-F(1207)





Specifications

Features:

- Hyper 612 ver. 2 generates only max 20 dB to provide a good operating environment.
- Without fans, the big fin area will give you dissipation for passive usage.
- Adopts the innovative patented CDC™ (Continuous Direct Contact) technology - side-by-side heat pipe configurations with no gaps creating a smooth surface for heat conduction.
- Folding fin design with good air guiding ensuring high efficiency heat dissipation.
- Quick-snap fan bracket design for simple installation.

Specifications:

© 2015 Respective owners and brand holders. This table has been carefully researched and generated by ComXpert International CC (http://www.comx.co.za), however, errors and omissions may occur. Only references to South Africa apply. All products are sourced in South Africa from the official suppliers and the warranty is that of the local supplier. E&OE. This table and our site's content may be used on condition that this notice and link remains intact and unaltered.

Specifications	
Product Code	RR-H6V2-13PK-R1
Supported Platforms	Intel LGA 2011-3/2011/1366/1156/1155/1150/775
	AMD FM2+/FM2/FM1/AM3+/AM3/AM2+/AM2
Heatsink Dimensions (LxWxH)	139 x 102 x 160.4 mm (5.5 x 4 x 6.3 inch)
Heatsink Material	6 Continuous Direct contact heatpipes / Aluminum fins
Heatsink Weight	732 g / 1.6 lb
Heatpipe Dimensions	Ø6 mm

Fan Dimensions (LxWxH)	120 x 120 x 25 mm (4.7 x 4.7 x 1 inch)
Fan Speed	800~1, 300 RPM +/-10%
Fan Air Flow	26.6 - 44.2 CFM (45.2 - 75 m3/h)+/-10%
Fan Air Pressure	0.6 - 1.6 mm H2O +/- 10%
Fan Life Expectancy	40,000 hrs 40
Noise Level	11-20 dBA
Bearing Type	Rifle bearing
Connector	4-Pin
Rated Voltage	12 VDC
Rated Current	0.09 A
Power Consumption	1.08 W
Fan Weight	154 g / 0.34 lb

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page:
https://www.comx-computers.co.za/RR-H6V2-13PK-R1-Coolermaster-Hyper-612-V2-CPU-Air-Cooler-p-111644.php

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: https://www.comx-computers.co.za/terms-of-use.php
Terms of Sale: https://www.comx-computers.co.za/terms-of-sale.php

PDF generated: 2026-11-21 10:23:06.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.