SAMSUNG HW-E6500

SAMSUNG HW-E6500 3D 1200W 5.2.Ch 3D Component System

Product Overview

Samsung, 3D Component System 1200W 5.2.Ch, 3D Component system, 3D Depth Sound, 2 x 10" subwoofers, HDMI 1.4, ARC, 2 way 3 speaker, USB, HDMI-in/out(2/1), Simple Speaker setup



Specifications

Features:

- USB 2.0 compatibility
- Auto sound calibration
- Bluetooth audio streaming
- AllShare
- Audio Return Channel (ARC)
- iPod/iPhone ready
- Vacuum tube technology

Specifications:

© 2013 Respective owners and brand holders. This table has been carefully researched and generated by ComXpert International CC (http://www.comx.co.za), however, errors and omissions may occur. Only references to South Africa apply. All products are sourced in South Africa from the official suppliers and the warranty is that of the local supplier. E&OE. This table and our site's content may be used on condition that this notice and link remains intact and unaltered.

Specifications	
Product Code	SAMSUNG HW-E6500
General Feature	
# of Channel (Amplifier)	7
# of Channel (DSP)	5.2
Frequency Range	20Hz ~ 20kHz
Power Consumption	116W
Reference THD / Impedence / Frequency	10% 4 ohm, 20Hz ~ 20kHz

Stand-by Power Consumption	0.9W
Total Power	150 x 5 + 150 x 2 = 1,050
Video Feature	
3D Video Pass	Yes
Auto AV Sync	No
Bi Amping	No
Deep Color / xvYCC	Yes
On Screen Display (OSD)	No
Video Up Conversion	No
Video Up-Scale	No
Audio Feature	
# of DSP	12
Auto Sound Calibration (ASC)	No
Dolby Digital	Yes
Dolby Digital EX	No
Dolby Digital Plus	No
Dolby Pro Logic II	Yes
Dolby Pro Logic IIx	No
Dolby Pro Logic IIz	No
Dolby True HD	No
DTS	Yes
DTS 96 / 24	No
DTS ES Discrete 6.1	No
DTS Neo 6	No
DTS HD Master Audio	No
Lip Sync	Yes
MP3 Enhancer	No
Multi-Ch PCM Processing	No
Smart Volume	No
Connectivity	
Anynet+ (HDMI-CEC)	Yes
ARC (Audio Return Channel)	Yes
Audio Input	3
Bluetooth	No
Component Input&Output	No
Digital Input (Optical / Coaxial)	2 / 1
Front A / V Inputs	1 A / V

HDMI Input&Output	2 / 1
Headphone Out	No
iPod / iPhone Dock Cradle included	No
Made for iPod / iPhone	No
Multi ch in	No
Multi ch out	No
USB Host	Yes
Tuner	
# of Preset	15
AM	No
FM	Yes
HD Radio	No
RDS	No
Special Feature	
Crystal Sound (Discrete Amp)	Pro
Energy Star	No
Speaker A / B	No
Speaker Assignable for Zone 2	No
Speaker	
Center	2 Way 3 Speaker (4" x 2 Woofer, Cone Tweeter w / Horn)
Front	2 Way 3 Speaker (6.5" x 2 Woofer, Cone tweeter w / Horn type)
Speaker Type	Wooden Tower SPK
Sub Woofer	1 Way 1 Speaker (10" Woofer)
Surround	2 Way 2 Speaker (4" Woofer, Cone Tweeter w / Horn)
Dimension&Weight	
Center Speaker (1-Piece) (WxHxD)	530 x 178 x 286mm
Center Speaker Weight (1-Piece)	4.3kg / EA
Front Speaker (WxHxD)	230 x 916 x 340mm
Front Speaker Weight	11.6kg / EA
Gross Dimension (WxHxD): One Packing	19.76 x 8.31 x 16.22in 502.0 x 211.0 x 412.0mm (Outside)
Gross Weight: One Packing	14.77lb (6.7kg)
Main Set Dimension (WxHxD)	16.93 x 6.46 x 14in 430.0 x 164.0 x 355.6mm
Main Set Weight	12.13lb (5.5kg)
Sub Woofer Net Dimension (WxHxD)	331 x 465 x 360mm
Sub Woofer Weight	8.7kg / EA

Surround Speaker Dimension (WxHxD)	178 x 530 x 286mm
Surround Speaker Weight	3.8kg / EA
Other Feature	
12V Trigger	No
Extra Feature	No
IR Port	No
Zone 2 Output (Line)	No

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page:
https://www.comx-computers.co.za/SAMSUNG-HW-E6500-SAMSUNG-HW-E6500-3D-1200W-5-2-Ch-3D-Component-System-p-83929.php

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: https://www.comx-computers.co.za/terms-of-use.php
Terms of Sale: https://www.comx-computers.co.za/terms-of-sale.php

PDF generated: 2026-11-21 01:43:29.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.