

SBW10A

PSS AVS SBW 10KVA 3 Phase Automatic Voltage Stabiliser, Servo-Motor Technology

Product Overview

PSS AVS SBW 10KVA 3 Phase Automatic Voltage Stabiliser, Servo-Motor Technology, High precision, Three phase, Analogue display, Variac design, Fully automatic, Minimal output wave distortion, Hi-efficiency, Overload protection, Accepts 20% voltage variations



PHASE		SINGLE PHASE		THREE PHASE			
Input voltage range		220V ±20% (can be set)		380V ±20%			
Output voltage range		220V ±5% (can be set)		380V ±5% (can be set)			
Frequency range		50Hz ~60Hz		50Hz ~60Hz			
Regulated precision		±0.1% ~ 0.5% (can be set)		±0.1% ~ 0.5% (can be set)			
Responding time		<0.5s		<0.5s			
Efficiency		>98%		>98%			
Ambient temperature		0 ~ 40°C		0 ~ 40°C			
Relative humidity		90%		90%			
Withstand voltage surges		1500VAC		2000VAC			
Insulation resistance		>5M ohm		>5M ohm			
MODEL	KVA RATING	STOCK CODE	DIMENSIONS (mm) (D x W x H)	DIMENSIONS (mm) (D x W x H)	Packaging	Kg Net	Kg GW
SINGLE PHASE							
TND-1K	1 KVA	AVS-501	210 x 160 x 145	265 x 240 x 180		5.5	5.9
TND-2K	2 KVA	AVS-502	290 x 200 x 230	365 x 290 x 230		9	10
TND-3K	3 KVA	AVS-503	290 x 240 x 230	410 x 410 x 230		24	26
TND-5K	5 KVA	AVS-505	365 x 220 x 230	450 x 300 x 240		16	19
TND-10K	10 KVA	AVS-5010	360 x 280 x 310	440 x 370 x 400		36	40
TND-20K	20 KVA	AVS-5020	420 x 380 x 350	510 x 470 x 420		70	75
TND-30K	30 KVA	AVS-5030	450 x 420 x 470	540 x 520 x 450		85	100
SINGLE PHASE COMBINATION REGULATOR							
TND-5K	5 KVA	AVS-705	380 x 320 x 190	460 x 400 x 400		41	50
TND-10K	10 KVA	AVS-710	440 x 360 x 190	520 x 450 x 400		68	76
TND-20K	20 KVA	AVS-720	520 x 400 x 460	610 x 490 x 460		85	96
TND-30K	30 KVA	AVS-730	600 x 460 x 470	680 x 550 x 470		91	102
TND-40K	40 KVA	AVS-740	640 x 570 x 1180	750 x 630 x 1200		175	192
TND-50K	50 KVA	AVS-750	640 x 570 x 1180	750 x 630 x 1200		185	192
TND-100K	100 KVA	AVS-7100	670 x 550 x 1320	780 x 650 x 1400		273	302
THREE PHASE AUTOMATIC REGULATOR							
SBW-20KVA	15 KVA	AVS-7020	1000 x 800 x 1370	1150 x 1000 x 1350		380	395kg
SBW-30KVA	20 KVA	AVS-7030	1000 x 800 x 1370	1150 x 1000 x 1350		400	415kg
SBW-40KVA	30 KVA	AVS-7040	1000 x 800 x 1370	1150 x 1000 x 1350		400	410kg
SBW-100KVA	100 KVA	AVS-70100	1700 x 800 x 1500	1900 x 1000 x 1500		580	610kg
SBW-150KVA	150 KVA	AVS-70150	1200 x 1000 x 1600	1300 x 1100 x 2000		704	800kg
SBW-250KVA	250 KVA	AVS-70250	1200 x 1000 x 1600	1300 x 1100 x 2100		875	910kg
SBW-500KVA	500 KVA	AVS-70500	1800 x 800 x 1970	1800 x 1000 x 2200	2-balcone	1820	2000kg

Specifications

Overview:

INTRODUCTION

Our Automatic Voltage Stabilizers are designed to work in the most rugged and temperamental conditions. They are best used in industrial environments such as mines and large factories, where low and high voltage conditions are experienced frequently. Our stabilizers range from 10 to 500 KVA. Rest assured, whatever your power conditions, there is a model for you!

APPLICATION

Computers, Copiers, Laboratories, Factories, High-Class Electrical Appliances, Embroidery Equipment, CNC Lathes, Automation Motors and Conveyor Belts

Features:

- High precision
- Three phase
- Analogue display
- Variac design
- Fully automatic
- Minimal output wave distortion
- Hi-efficiency
- Overload protection
- Accepts 20% voltage variations

Specifications:

ComX Computers

Product Specification Sheet

© 2017 Respective owners and brand holders. This table has been carefully researched and generated by ComXpert International CC (<http://www.comx.co.za>), however, errors and omissions may occur. Only references to South Africa apply. All products are sourced in South Africa from the official suppliers and the warranty is that of the local supplier. E&OE. This table and our site's content may be used on condition that this notice and link remains intact and unaltered.

Specifications

Product Code	SBW10A
Technology	Servo-Motor
Size	10KVA -2000KVA
Input/output Voltage	400V/400V
Design	Tower

Product Information Online

For the latest product information, availability and purchasing details, please visit the product page:

Product page:

<https://www.comx-computers.co.za/SBW10A-PSS-AVS-SBW-10KVA-3-Phase-Automatic-Voltage-Buy-p-169892.php>

Images and specifications are provided for reference and are subject to change without notice. E&OE.

Terms of Use: <https://www.comx-computers.co.za/terms-of-use.php>

Terms of Sale: <https://www.comx-computers.co.za/terms-of-sale.php>

PDF generated: 2026-10-09 07:54:03.

This PDF was generated automatically and may include content prepared or assisted by automated or AI-based systems. While reasonable care is taken to ensure accuracy, errors or omissions may occur.

For the most current and accurate product information, please refer to the product information available on our website. If any specification or other information differs from information published elsewhere, please confirm the details with us before relying on the information or making a purchasing decision.

If you identify an error or discrepancy, please report it to us so that we may investigate and correct it where necessary.